No. SS2-GTX00A-0100 **Specification** azbi

# Advanced Transmitter Absolute Pressure Transmitters

Model GTX30A/GTX60A

# **OVERVIEW**

Advanced Transmitter is a microprocessor-based smart transmitter that features high performance and excellent stability. Capable of measuring gas, liquid, vapor, and liquid levels, it transmits 4 to 20 mA DC analog and digital signals according to the measured pressure.

It can also execute two-way communications between the communicator, thus facilitating self-diagnosis, range resetting, and automatic zero/span adjustment.

SFN, HART and FOUNDATION Fieldbus are available.

\* Refer to SS2-GTX00Z-0100 for FOUNDATION Fieldbus type for the items marked with [\*].

# **FEATURES**

#### **Excellent stability and high performance**

- Our proven sensor technology enables Long-term stability.
- Unique characterization and composite semiconductor sensors realize excellent temperature and static pressure characteristics.

# Wide measuring range (rangeability)

A wide measuring range is available from a single model. This feature is highly effective in taking measurements over a wide range and reducing the need for inventory.

\* Model GTX60A: 35 to 3500 kPa abs. (range ability: 1 to100)

### A diverse lineup

- A wide range of models is available to meet user needs for low, standard, and high pressures.
- A wide variety of corrosion-resistant materials for wetted parts is also available.



#### **Remote communication**

Two-way communication using digital output facilitates selfdiagnosis, range resetting, automatic zero adjustment, and other operations.

# PRODUCT APPROVALS [\*]

# FM Explosionproof for Division System/ Flameproof for Zone System (Code F1)

Explosionproof for Class I, Division 1, Groups A, B, C and D; Class I, Zone 1, AEx d IIC Dust-Ignitionproof for Class II, III, Division 1, Groups E, F and G

T5 –40 °C  $\leq$  Tamb $\leq$  +85 °C Hazardous locations Indoor/Outdoor Type 4X, IP67 Factory sealed, conduit seal not required for Division applications Caution - Use supply wires suitable for 5 °C above surrounding ambient

# FM Intrinsic Safety (Code F2)

IS/I, II, III/1/ABCDEFG/T4;  $-40 \text{ °C} \le \text{Tamb} \le +60 \text{ °C}$ ; 80395278, 80395279, 80395280; Entity; TYPE 4X; IP67 I/0/AEx ia/IIC/T4;  $-40 \text{ °C} \le \text{Tamb} \le +60 \text{ °C}$ ; 80395278, 80395279, 80395280; Entity; TYPE 4X; IP67 Entity Parameters: Vmax (Ui)=30 Volts, Imax (Ii)=100 mA, Pi=1 W, Ci=10 nF, Li=0.5 mH

# FM Nonincendive (Code F5)

NI/I/2/ABCD/T4;  $-40 \degree C \le T_{amb} \le +60 \degree C$ ; 80395494; NIFW; TYPE 4X; IP67 NI/I/2/IIC/T4;  $-40 \degree C \le T_{amb} \le +60 \degree C$ ; 80395494; NIFW; TYPE 4X; IP67 S/II, III/1/EFG/T4;  $-40 \degree C \le T_{amb} \le +60 \degree C$ ; 80395494; NIFW; TYPE 4X; P67 Nonincendive Field Wiring Parameters: Vmax (Ui)=30 Volts, Ci=10 nF, Li=0.5 mH

# Combination of F1, F2 and F5 (Code F6)

# **ATEX Flameproof and Dust Certifications**

# (Code A1)



II 1/2 G Ex db IIC T6 Ga/Gb -30 °C $\leq$ Tamb $\leq$ +75 °C Tprocess $\leq$ 85 °C II 1/2 G Ex db IIC T5 Ga/Gb -30 °C $\leq$ Tamb $\leq$ +80 °C Tprocess $\leq$ 100 °C II 1/2 G Ex db IIC T4 Ga/Gb -30 °C $\leq$ Tamb $\leq$ +80 °C Tprocess $\leq$ 110 °C II 2 D Ex db IIC T85 °C Db -30 °C $\leq$ Tamb $\leq$ +75 °C Tprocess $\leq$ 85 °C II 2 D Ex tb IIIC T100 °C Db -30 °C $\leq$ Tamb $\leq$ +75 °C Tprocess $\leq$ 100 °C II 2 D Ex tb IIIC T110 °C Db -30 °C $\leq$ Tamb $\leq$ +75 °C Tprocess $\leq$ 110 °C Caution - Use supply wires suitable for 5 °C above surrounding ambient

# **ATEX Intrinsic Safety and Dust Certifications**

# (Code A2)



 $\{ \mathbf{x} \}$  KEMA 07ATEX0200 X

II 1 G Ex ia IIC T4 Ga -30 °C≤Tamb≤+60 °C Tprocess=105 °C IP66/IP67

ELECTRICAL PARAMETERS: Ui=30V, li=93mA, Pi=1W, Ci=5nF, Li=0.5mH

II 1 D Ex ia IIIC T105 °C Da -30 °C≤Tamb≤+60 °C Tprocess=105 °C IP66/IP67

II 3 G Ex ic IIC T4 Gc -30 °C $\leq$ Tamb $\leq$ +60 °C Tprocess=110 °C

IP66/IP67

ELECTRICAL PARAMETERS: Ui=30V, Ci=5nF, Li=0.5mH

# **NEPSI Flameproof and Dust Certifications**

## (Code N1)

Ex d IIC T6 Gb; Ex tD A21 IP66/IP67 T85 °C Tprocess= 80 °C; -30 °C $\leq$ Tamb $\leq$ +75 °C Ex d IIC T5 Gb; Ex tD A21 IP66/IP67 T100 °C Tprocess= 95 °C; -30 °C $\leq$ Tamb $\leq$ +80 °C Ex d IIC T4 Gb; Ex tD A21 IP66/IP67 T115 °C Tprocess= 110 °C; -30 °C $\leq$ Tamb $\leq$ +80 °C

# **NEPSI Intrinsic Safety Certification (Code N2)**

Ex ia IIC T4 Ga -40 °C≤Tamb≤+60 °C Tprocess=105 °C IP66/IP67

Ex ic IIC T4 Gc -40 °C ≤ Tamb ≤ +60 °C Tprocess = 110 °C IP66/IP67

ELECTRICAL PARAMETERS: Ui=30V, li=100mA, Pi=1W, Ci=13nF, Li=0.5mH

Use cable suitable for 5 °C above ambient temperature

# IECEx Flameproof and Dust Certifications(Code E1)

Certificate No. IECEx KEM 08.0001 X

Ex db IIC T6 Ga/Gb -30 °C $\leq$ Tamb $\leq$ +75 °C Tprocess $\leq$ 85 °C Ex db IIC T5 Ga/Gb -30 °C $\leq$ Tamb $\leq$ +80 °C Tprocess $\leq$ 100 °C Ex db IIC T4 Ga/Gb -30 °C $\leq$ Tamb $\leq$ +80 °C Tprocess $\leq$ 110 °C Ex tb IIIC T85 °C Db -30 °C $\leq$ Tamb $\leq$ +75 °C Tprocess $\leq$ 85 °C Ex tb IIIC T100 °C Db -30 °C $\leq$ Tamb $\leq$ +75 °C Tprocess $\leq$ 100 °C

Ex tb IIIC T110 °C Db -30 °C $\leq$ Tamb $\leq$ +75 °C T<br/>process $\leq$  110 °C

Caution - Use supply wires suitable for 5  $^{\rm o}{\rm C}$  above surrounding ambient

# IECEx Intrinsic Safety and Dust Certifications(Code E2)

Certificate No. IECEX KEM 07.0058 X Ex ia IIC T4 Ga -30 °C≤Tamb≤+60 °C Tprocess=105 °C IP66/IP67 ELECTRICAL PARAMETERS: Ui=30V, li=93mA, Pi=1W, Ci=5nF, Li=0.5mH Ex ia IIIC T105 °C Da -30 °C≤Tamb≤+60 °C Tprocess=105 °C IP66/IP67 Ex ic IIC T4 Gc -30 °C≤Tamb≤+60 °C Tprocess=110 °C IP66/IP67 ELECTRICAL PARAMETERS: Ui=30V, Ci=5nF, Li=0.5mH

# KCs Flameproof (Code K1) 11-AV4BO-0323

Ex d IIC T6 -30 °C≤Tamb≤+75 °C Tprocess=85 °C Ex d IIC T5 -30 °C≤Tamb≤+80 °C Tprocess=100 °C Ex d IIC T4 -30 °C≤Tamb≤+80 °C Tprocess=110 °C

### **Azbil Corporation**

#### 18-AV4BO-0254X

Ex tD A21 T85 °C -30 °C≤Tamb≤+75 °C -30 °C≤Tprocess≤85 °C

Ex tD A21 T100 °C -30 °C≤Tamb≤+75 °C -30 °C≤Tprocess≤100 °C

Ex tD A21 T110 °C -30 °C≤Tamb≤+75 °C -30 °C≤Tprocess≤110 °C

# TIIS Flameproof (Code J1)

Ex d IIC T4

Use cables with the maximum allowable temperature, 70° C in case ambient temperature excess 50° C

## **TAIWAN Flameproof (Code T1)**

Certificate No.(2015)00113

Ex db IIC T6 Gb X -30° C≤ Tamb ≤+75° C Tprocess≤85 °C

Ex db IIC T5 Gb X -30° C<br/>≤ Tamb ≤+80° C T<br/>process≤100 °C

Ex db IIC T4 Gb X -30° C $\leq$  Tamb  $\leq$ +80° C Tprocess $\leq$ 110 °C

Caution - Use supply wires suitable for 5  $^{\rm o}{\rm C}$  above surrounding ambient

Please refer to specification, "SS2-GTX00Z-0100" for the Fieldbus code below.

# FM Intrinsic safety ia/ic FISCO and Fieldbus(Code F4)

#### FM Fieldbus Nonincendive(Code F7)

ATEX Intrinsic safety ia FISCO and Fieldbus(Code A4)

ATEX Intrinsic safety ic FISCO and Fieldbus(Code A7)

IECEx Intrinsic safety ia FISCO and Fieldbus(Code E4)

IECEx Intrinsic safety ic FISCO and Fieldbus(Code E7)

### EMC Conformity [★]

EN 61326-1 (industrial electromagnetic environment) EN 61326-2-3

# FUNCTIONAL SPECIFICATIONS

# Type of protection

NEMA 3 and 4X IEC IP66/67

#### Measuring span/Setting range

Model	Measuring Span	Setting Range
GTX30A	4 to 104 kPa abs {30 to 780 mmHg abs}	0 to 104 kPa abs {0 to 780 mmHg abs}
GTX60A	35 to 3500 kPa abs {0.35 to 35 kgf/cm <sup>2</sup> abs}	0 to 3500 kPa abs {0 to 35 kgf/cm <sup>2</sup> abs}

# Working Pressure Range/Overload Resistance value

Model	Working Pressure Range	Overload Resistance value
GTX30A	0.01 to 104 kPa abs {0.1 to 780 mmHg abs} See Figure 1	300 kPa abs {3.0 kgf/cm² abs}
GTX60A	0.01 to 3500 kPa abs {0.1 mmHg abs to 35 kgf/cm <sup>2</sup> abs} See Figure 1	5250 kPa abs {52.5 kgf/cm² abs}

*Note)* With PVC wetted parts, the maximum working pressure is 1.5 MPa {15 kgf/cm<sup>2</sup>}.







Figure 2. Working pressure and temperature of wetted parts section (for oxygen and chlorine service models)

### Power Supply [★]

12.5 to 42 V DC Limited to 12.5 to 30 V DC for intrinsic safety, Nonincendive types

### Power Supply voltage and load resistance

No. SS2-GTX00A-0100

3

# characteristics [\*]

#### See Figure 3.

Limited to Load resistance: 250 to 1345  $\Omega$  for SFN or DE communication. 250 to 600  $\Omega$  for HART communication. Power supply voltage: 12.5 to 30 V DC for intrinsic safety, Nonincendive types



#### Figure 3. Supply voltage vs. load resistance characteristics

Note) For communication with a communicator, a load resistance of  $250 \Omega$  or more is necessary.

# Output [\*]

Analog output (4 to 20 mA DC) with DE protocol Analog output (4 to 20 mA DC) with HART protocol Digital output (DE protocol)

# Output signal [\*]

3.6 to 21.6 mA 3.8 to 20.5 mA (NAMUR NE43 compliant)

# Failure Alarm [\*]

Upper: 21.6 mA or more Lower: 3.6 mA or less

### Ambient temperature limit

#### Normal operating range

-40 to +85 °C for general purpose models
-10 to +75 °C for oxygen and chlorine models
-25 to +80 °C for models with digital indicators
Meterbody cover material PVC : 0 to 55 °C
-20 to +60 °C for TIIS explosion proof model

### **Operative limits**

- -50 to +93 °C for general purpose models
- -40 to +80 °C for oxygen and chlorine models
- -30 to  $+85\ ^{\rm o}{\rm C}$  for models with digital indicators
- -10 to +60 °C for models with PVC meterbody covers
- -20 to +60 °C for TIIS explosion proof model

### **Transportation and storage conditions**

Without indicators : -50 to +85 °C With indicators : -25 to +80 °C -10 to +60 °C for models with PVC meterbody covers

### **Temperature ranges of wetted parts**

#### Normal operating range

-40 to +110 °C for general purpose models -20 to +75 °C for oxygen and chlorine models 0 to 55 °C for models with PVC meterbody covers -20 to +110 °C for TIIS explosion proof model

#### **Operative limits**

- -50 to +115 °C for general purpose models
- -40 to +80 °C for oxygen and chlorine models
- -10 to +60 °C for models with PVC meterbody covers
- -20 to +110 °C for TIIS explosion proof model

### **Ambient humidity limits**

5 to 100 % RH

# Stability against supply voltage change

 $\pm 0.005$  % FS/V

## Response time [\*]

Below 100 msec. (when damping time is set to 0 sec.)

## Damping time [\*]

Selectable from 0 to 128 sec. (HART) Selectable from 0 to 32 sec. in ten stages (SFN)

## **Zero Stability**

 $\pm$  0.2% of URL per 10-year

# Lightning protection [\*]

Applicable Standards; IEC 61000-4-5 Peak value of current surge (80/20 μ sec.): 6000 A

### **Vibration characteristics**

Amplitude: 0.42 mm / Frequency: 5 to 60 Hz Acceleration: 29.4 m/s<sup>2</sup> (3G)/60 to 200 Hz

# **Shock characteristics**

Acceleration 9.8 m/s<sup>2</sup> (1G)

### Indicator

The digital LCD indicator (optional) shows the output in percentage or in engineering units. Range for engineering unit is from -99999 to 99999 when set at the factory, and from -19999 to 19999 when using the communicator. Specify the following items when placing order with engineering units,

- Pressure range
- Engineering unit of pressure
- Method of display, either linear or square-root.

These data may be set or changed using the communicator.

# **OPTIONAL SPECIFICATIONS**

#### **Oil free finish**

The transmitter is shipped with oil-free wetted parts.

### Adapters for anticorrosion materials

These are adaptor flanges to connect 82 mm pipes made of anticorrosion materials [excluding ASTM B575 (Equivalent to Hastelloy C-276)] to 54 mm general-purpose pipes.

### External zero/span adjustment function

The transmitter can be easily adjusted to zero or span in the field.

# **Azbil Corporation**

## Elbow

This is an adaptor for changing the electrical conduit connection port from the horizontal to the vertical direction, if required by wiring conditions in the field. One or two elbows may be used as needed.

# **Conformance to Non SI units**

We deliver transmitters set to any Non SI units as specified.

# **Safety Transmitter**

Select this option to be used as a component of Safety Instrument System (SIS).

Models GTX\_ \_ \_ is complied with IEC61508, certified according to Safety Integrity Level 2 (SIL-2)

This option is not applicable for FOUNDATION Fieldbus type, DE communication type, external zero/span adjustment (option A2), and Alarm output (option Q7).

# Alarm Output (contact output)

Contact output is prepared as alarm output when alarm (Output Alarm/Sensor Temp. Alarm) condition is detected. It can be set to or Normally Close.

Contact output type : One open collector (NPN) Contact rating: 30 V DC max., 30 mA DC max. Residual voltage at output ON: 3.0 V max. Operating mode: Normally Open (default)

Normally Close is not recommended. When this option is selected, CHECK terminals for current check cannot be used.

This option is not applicable for FOUNDATION Fieldbus type, and with intrinsic safety, Nonincendive types.

# Advanced diagnostics [\*]

This option is applicable for FOUNDATION Fieldbus type. Refer to SS2-GTX00Z-0100.

# **Custom calibration**

Calibrate for the specified pressure range at the factory.

# Long vent drain:

Maintenance, process conditions, and safety are addressed by using a drain whose length (60 mm) is longer than the standard length (27 mm).

# Moisture-free finish (including oil-free finish):

Shipped with water content and oil content removed from the wetted part. (A small amount of fluorine oil is applied to vent/drain plugs in order to prevent sticking.)

# **Test report:**

Shows the results of having tested the appearance, input output characteristics, insulation resistance, dielectric strength, etc., of the transmitter.

### Mill sheet:

Shows data related to the chemical composition, heat treat-

ment condition, and mechanical properties of the wetted part material.

## Test report (with traceability certificate):

Comprised of three documents: a traceability diagram, a calibration certificate, and a test report.

# Withstand pressure and air tight test (general-purpose use):

Shows the results of the wetted part withstand pressure test (10 minutes) and air tight test (10 minutes).

# Strength calculation sheet:

Shows the results of having calculated the strength of the meter body cover, flanges, and bolts.

## Materials

### Fill fluid

Silicone oil for general purpose and high-temperature vacuum models

Fluorine oil for oxygen and chlorine models

#### **Center body**

316 SST

#### Transmitter case

Aluminum alloy, CF8M (Equivalent to 316 SST)

#### Meter body cover SCS14A (equivalent to 316 SST) or PVC

#### **Bolts and nuts (for fastening meter body cover)** Carbon steel (SNB7), 304 SST, 316 SST, 630 SST

# O-ring

NBR

## For Wetted parts

## Adapter flange (option) SCS14A (Equivalent to 316 SST), PVC

### **Center body**

316 SST (Diaphragm 316L SST) ASTM B575 (Hastelloy C-276 equivalent), Tantalum, 316L SST

#### Vents and plugs

316 SST, PVC

#### Gaskets PTFE

#### Mounting Bracket Bracket 304 SST

U-bolt and nuts 304 SST

### Paint

Standard: Baked acrylic paint Corrosion-proof: Baked urethane paint

### Color

Housing: Silver N-8.2

Cap: azbil bordeaux 2.5R 2.25/5

# Weight

Approx. 3.4 kg

# INSTALLATION

## **Electrical connection**

G 1/2 internal thread, 1/2 NPT internal thread, M20 internal thread.

## Grounding

Resistance 100  $\Omega$  max.

# Mounting

Can be installed on a 2-inch horizontal or vertical pipe (can be directly mounted on a process pipe)

### **Process connection**

Rc 1/2, 1/2 NPT internal thread and Rc 1/4, 1/4 NPT internal thread.

# **TRANSMITTER HANDLING NOTES**

To get the most from the performance this transmitter can offer, please use it properly noting the points mentioned below. Before using it, please read the Instruction Manual.

# **Transmitter installation notes**

#### WARNING

- When installing the transmitter, ensure that gaskets do not protrude from connecting points into the process (such as adapter flange connection points and connecting pipes and flanges). Failure to do so may cause a leak of process fluid, resulting in harm from burns, etc. In addition, if the process fluid contains toxic substances, take safety measures such as wearing goggles and a mask to prevent contact with the skin and eyes and to prevent inhalation.
- Use the transmitter within the operating ranges stated in the specifications (for explosion-proofing, pressure rating, temperature, humidity, voltage, vibration, shock, mounting direction, atmosphere, etc.). Using the transmitter outside the operating conditions may cause device failure or fire, resulting in a harmful physical risk of burning or the like.
- When performing wiring work in explosion-proof areas, follow the work method specified in the explosion-proof guidelines.

# 

- After installation, do not use the transmitter as a foothold or put your weight on it. Doing so may cause damage.
- Be careful not to hit the glass indicator with tools etc. This could break the glass and cause injury.
- The transmitter is heavy. Wear safety shoes and take care when installing it.
- Impact to transmitter can damage sensor module.

# Wiring notes

#### WARNING

• To avoid shocks, do not perform electrical wiring work with wet hands or with live wires.

### 

- Do wiring work properly in conformance with the specifications. Wiring mistakes may result in malfunction or irreparable damage to the instrument.
- Use a power supply that conforms to the specifications. Use of an improper power supply may result in malfunction or irreparable damage to the instrument.
- Use a power supply with overcurrent protection for this instrument.

# Handling precautions for HART specification devices

- If you need to operate with a secondary host (HART communicator, etc.), set the communication interval of the primary host (DCS, device management system) to 8 seconds or more, or suspend communication from the primary host. If the primary host repeats HART communication within 8 seconds, the request from the secondary host may not be received (communication may not be possible).
- If electrical noise in the environment prevents HART communications with the host, take countermeasures such as separating the signal cables from the source of the noise, improving the grounding, changing to shielded signal cables, etc. Even if noise interferes with HART communications, the 4–20 mA analog signal will be unaffected and can be used for control.
- If this product is being operated in multidrop mode, there is a limit to the number of devices that can be used. If you are using multidrop mode, please consult with us.

# **PERFORMANCE SPECIFICATIONS**

#### **Reference accuracy**

Shown for each item are the percentage ratio for x (kPa), which is the greatest value of either the upper range value (URV)<sup>\*1</sup>, the lower range value (LRV)<sup>\*2</sup> or the span.

# Model GTX30A

Material of wetted parts: Diaphragm; 316L SST, Others; 316 SST

Reference accuracy *3 *4		±0.15 %	(For <i>x</i> ≥12 kPa abs {90 mmHg abs})
		$\pm (0.05+0.1 \times \frac{12}{x})\%$	(For x<12 kPa abs {90 mmHg abs})
Ambient Temperature effect	Combined shift:	±1.2 %	(For <i>x</i> ≥12 kPa abs {90 mmHg abs})
(Shift from the set range) Change of 30 °C *3	(including zero and span shifts)	$\pm (0.35+0.85 \times \frac{12}{x})\%$	(For <i>x</i> <12 kPa abs {90 mmHg abs})

# Model GTX30A

Material of wetted parts: Diaphragm; ASTM B575 (Hastelloy C-276 equivalent), Tantalum, 316L SST Others; ASTM B575 (Hastelloy C-276 equivalent), Tantalum, 316L SST

Reference accuracy *3 *4		±0.35 %	(For $x \ge 12$ kPa abs {90 mmHg abs})
		$\pm (0.25+0.1 \times \frac{12}{x})\%$	(For x<12 kPa abs {90 mmHg abs})
Ambient Temperature effect	Combined shift:		
(Shift from the set range)	(including zero and span shifts)	$\pm (0.55+1.85\times\frac{24}{r})\%$	
Change of 30 °C *3		$\pm (0.55 + 1.85 \times \frac{1}{x})\%$	
(Range from –5 to 55 °C)			

# Model GTX60A

Material of wetted parts: Diaphragm; 316L SST, Others; 316 SST

Reference accuracy *3 *4		±0.15 %	(For $x \ge 350$ kPa abs {3.5 kgf/cm <sup>2</sup> abs})
		$\pm (0.05+0.1 \times \frac{350}{x})\%$	(For <i>x</i> <350 kPa abs {3.5 kgf/cm <sup>2</sup> abs})
Ambient Temperature effect	Combined shift:	±1.2 %	(For $x \ge 350$ kPa abs {3.5 kgf/cm <sup>2</sup> abs})
(Shift from the set range) Change of 30 °C *3	(including zero and span shifts)	$\pm (0.35+0.85 \times \frac{350}{x})\%$	(For <i>x</i> <350 kPa abs {3.5 kgf/cm <sup>2</sup> abs})

# Model GTX60A

Material of wetted parts: Diaphragm; ASTM B575 (Hastelloy C-276 equivalent), Tantalum, 316L SST Others; ASTM B575 (Hastelloy C-276 equivalent), Tantalum, 316L SST

Reference accuracy *3 *4		±0.35 %	(For $x \ge 350$ kPa abs {3.5 kgf/cm <sup>2</sup> abs})
		$\pm (0.25+0.1 \times \frac{350}{x})\%$	(For <i>x</i> <350 kPa abs {3.5 kgf/cm <sup>2</sup> abs})
Ambient Temperature effect	Combined shift:	±1.5 %	(For $x \ge 350$ kPa abs {3.5 kgf/cm <sup>2</sup> abs})
(Shift from the set range)	(including zero and span shifts)		_
Change of 30 °C *3		$\pm (0.35+1.15 \times \frac{350}{r})\%$	(For <i>x</i> <350 kPa abs {3.5 kgf/cm <sup>2</sup> abs})
(Range from –5 to 55 °C)		× x ′	-

\*1. URV denotes the process value for 100 % (20 mA DC) output.

\*2. LRV denotes the process value for 0 % (4 mA DC) output.

\*3. Within a range of URV $\geq 0$  and LRV $\geq 0$ .

*\*4. Reference accuracy at calibrated condition.* 

# **MODEL SELECTION**

## Model GTX30A (Standard absolute pressure) Model GTX60A (High absolute pressure)

Model No.: GTX\_\_A - Selection I (I II III IV V VI VII) - Selection II (I II III IV V VI) - Option

#### Basic Model No.

24010			
		4.0 to 104 kPa abs. (30 to 780 mmHg)*1	GTX30A
l	Measuring span	35 to 3500 kPa abs. (0.35 to 35 kgf/cm <sup>2</sup> )*2	GTX60A

#### Selection I

Selec	ction I									
Ι	Output	4 to 20 mA (SFN Communication)								
				В						
				С						
		Digital output (DE com	munication) *3	D						
		4 to 20 mA (HART7 Co	mmunication)	F						
II	Fill fluid	Regular type (Silicone o	il)		Α					
		For oxygen service (Flue	orine oil)		Н					
		For chlorine service (Flu	iorine oil) *4		J					
III	Material (Meterbody	Meterbody cover	Vent/Drain plugs							
	cover, Vent/Drain plugs)	SCS14A	316 SST			А				
		PVC *5 *6 *7 *8 *12	PVC *5 *6 *7 *8 *12			С				
IV	Material (center body)	316 SST (Diaphragm: 316L SST) A								
		ASTM B575 (Equivalent	t to Hastelloy C-276)*9				В			
		Tantalum *9 *10					С			
		316L SST *10					D			
V	Process connections	Rc 1/2, with adapter flar	nge *7					А		
		Rc 1/4, with adapter flar	nge					В		
		Rc 1/4, without adapter	flange					С		
		1/2 NPT internal thread, with adapter flange *7				D				
		1/4 NPT internal thread	, with adapter flange					Е		
		1/4 NPT internal thread	, without adapter flange					F		
VI	Process installation	Vertical piping, top cont	nection *8 *9						Α	
		Vertical piping, bottom	connection *8 *9						В	
		Horizontal piping, front	connection						С	
VII	Bolt/nut	Carbon steel								Α
		304 SST								В
		630 SST								С
		316 SST *11								D

\*1. Specify range in abs. Pressure. Correct: 0 to 500 mmHg abs. Incorrect: -700 mmHg to 1 kgf/cm<sup>2</sup>.

\*2. Specify range in abs. Pressure. Correct: 0 to 3 kgf/cm<sup>2</sup> abs. Incorrect: -1 to 2 kgf/cm<sup>2</sup> abs.

\*3. Not applicable for the combination with code A2 "With external Zero/Span adjustment", Q1 "Safety Transmitter", and Q2 "NAMUR NE43 Compliant Output signal limits" of Option.

- \*4. In case code J is selected, code C "Tantalum" of Material (Centerbody) should be selected.
- \*5. 304 SST bolts and nuts material (-B) must be selected when PVC meterbody cover is selected (-C). The max. working pressure is 1.5 MPa.
- \*6. Applicable for wetted parts of center body material; ASTM B575 or Tantalum.
- \*7. In case PVC is selected, code A, or D of Process connections should be selected.
- \*8. In case PVC is selected, code A, or B of Process installation should be selected.
- \*9. Code A, or B of Process installation should be selected.
- \*10. Not applicable for the combination with code D of Bolt/nut.
- \*11. In case this code is selected, code P8 of Option code should be selected.
- \*12. In case PVC is selected, Not applicable for the combination with code T2 "Mill certificate" of Option code.
- \*13. Not applicable for the combination with code Q1 "Safety Transmitter" and Q2 "NAMUR NE43 Compliant Output signal limits" of Option.
- \*14. In case code A of indicator is selected, code A2 of Option code should be selected.
- \*15. Not applicable for the combination with code YB "Manufactured by ACNP (for use in China)" and YD "Manufactured by ACNP( for use outside of China)" of Option.

Г

#### Model No.: GTX\_ \_A - Selection I (I II III IV V VI VII) - Selection II (I II III IV V VI) - Option

## Selection II

Ι	Electrical connection	G1/2 *2 *13	1				
		G1/2 TIIS explosion proof with 1 cable gland attached *3 *13	3				
		G1/2 TIIS explosion proof with 2 cable gland attached *3 *13	4				
		1/2 NPT, Watertight	Α	1			
		M20, Watertight *1	В	1			
II	Explosion proof [*] *14 *15	None		XX			
	Internet	FM Explosionproof for Division system/Flameproof for Zone system		F1			
		FM Intrinsic safety		F2			
		FM Intrinsic safety ia/ic FISCO and Fieldbus *8		F4			
		FM Nonincendive		F5			
		Combination of code F1, F2, and F5		F6			
		FM Fieldbus Nonincendive *8		F7			
		ATEX Flameproof		A1			
		ATEX Intrinsic safety		A2			
		ATEX Intrinsic safety ia FISCO and Fieldbus *8		A4			
		ATEX Intrinsic safety ic FISCO and Fieldbus *8		A7			
		IECEx Flameproof		E1			
		IECEx Intrinsic safety		E2			
		IECEx Intrinsic safety ia FISCO and Fieldbus *8		E4			
		IECEx Intrinsic safety ic FISCO and Fieldbus *8		E7			
		NEPSI Flameproof		N1			
		NEPSI Intrinsic safety		N2			
		TIIS Flameproof *5 *6		J1			
		KCs Flameproof *6		K1			
		TAIWAN Flameproof		T1			
III	Indicator	None		X			
		With indicator *7		A			
IV	Paint *12	Standard			Х		
		None (316 stainless steel housing) *4			E		
		Corrosion-proof (Urethane)			Н		
V	Failure alarm	Upper limit of output at abnormal condition			÷.	A	٦
		Lower limit of output at abnormal condition				В	7
		None (for FOUNDATION Fieldbus) *8				X	7
VI	Mounting bracket	None					
		CF8 (L form) *9					
		CF8M (L form) *9 *11					
		304 SST (Flat form) *10					

\*1. Not applicable for the combination with code F1, F6 of Explosion proof.

- \*2. Code XX of Explosion proof should be selected.
- \*3. Code J1 of Explosion proof should be selected.
- \*4. Not applicable for combination with code 1,3,4 of Electrical connection.
- \*5. 3 or 4 of Electrical connection should be selected.
- \*6. Not applicable for the combination with code E of Paint.
- \*7. In case the code C "FOUNDATION Fieldbus communication" of output is selected, code A2 of Option code should be selected.
- \*8. In case this code is selected, code *C* of Output should be selected.
- \*9. Applicable for wetted parts of centerbody material, 316 SST.
- \*10. Applicable for wetted parts of centerbody material, ASTM B575, Tantalum, 316L SST.
- \*11. In case this code is selected, code P8 of Option code should be selected.
- \*12. In case code X or H is selected, the material of transmitter case is aluminum alloy.
- \*13. Not applicable for the combination with code YB "Manufactured by ACNP (for use in China)" and YD "Manufactured by ACNP( for use outside of China)" of Option.
- \*14. For FOUNDATION Fieldbus type. Refer to SS2-GTX00Z-0100.
- \*15. For option code YB "Manufactured by ACNP (for use in China)" and YD "Manufactured by ACNP( for use outside of China)" selected, only the following codes can be selected. YB: XX, N1, N2 YD: YX, EL E2, E5, E6, A1, A2, E1, E2, T1

YD: XX, F1, F2, F5, F6, A1, A2, E1, E2, T1

Model No.: GTX\_\_A - Selection I (I II III IV V VI VII) - Selection II (I II III IV V VI) - Option

Option	—	
	No options	XX
	With external Zero/Span adjustment *8 *9	A2
	One elbow (left) *3 *4 *7	G1
	One elbow (right) *3 *4 *7	G2
	2 elbows *3 *5 *7	G3
	Long vent/drain plugs	G4
	Side vent/drain top *3	G6
	Side vent/drain bottom *3	G7
	Oil and water free finish	K1
	Oil free finish *1	K3
	316 SST (Parts in contact with atmosphere) *11 *12 *13	P8
	Safety Transmitter *2 *9 *14 *16	Q1
	NAMUR NE43 Compliant Output Signal Limits: 3.8 to 20.5 mA (Output 21.6 mA/selected upper limit, 3.6 mA/selected lower limit) *9 *14	Q2
	Alarm Output (contact output) *10 *14	Q7
	Advanced diagnostics *15	Q8
	Custom calibration	R1
	Test report	T1
	Mill certificate	T2
	Traceability certificate *17	T4
	NACE certificate *6	T5
	Non SI Unit	W1
	Safety label for Taiwan	Y2
	Manufactured by ACNP (for use in China)	YB
	Manufactured by ACNP( for use outside of China)	YD

\*1. No need to select when Fill Fluid code H, or J is selected.

\*2. Not applicable for the combination with code A2, or Q7 of Option.

\*3. Not applicable for the combination with code A, or B of Process installation.

\*4. Not applicable for the combination with code F1, F6 of Explosion proof.

\*5. Not applicable for any Explosion proof. Please select code XX "None" of Explosion proof.

- \*6. Applicable for "ASTM B575", code B of Material (center body).
- \*7. Not applicable for the combination with code B "M20, Watertight" electrical connection.
- \*8. Not applicable for the combination with code X "None" of Indicator. Please select "With indicator".
- \*9. Not applicable for the combination with code D "Digital output (DE communication)" of output.
- \*10. Not applicable for the combination with code F2, F5, F6, N2, C2, E2, and A2 of Explosion proof.

\*11. In case code P8 is selected, code D of Bolt/nut should be selected.

\*12. In case code P8 is selected, code E of Paint should be selected.

\*13. In case code P8 is selected, code X or 2 of Mounting bracket should be selected.

\*14. Not applicable for the combination with code C "Digital output (FOUNDATION Fieldbus communication)" of output.

- \*15. Not applicable for the combination with code A "4 to 20 mA (SFN Communication)", B "4 to 20 mA (HART5 Communication)", and D "Digital output (DE communication)" of output.
- \*16. Not applicable for the combination with code F "HART7 comunication" of output.
- \*17. Not applicable for the combination with code YB "Manufactured by ACNP (for use in China)" and YD "Manufactured by ACNP( for use outside of China)" of Option.

# **DIMENSIONS** Model GTX30A/60A (Material (center body): 316 SST)

Process connection: Front side





Process Connection: Top or bottom side





# Model GTX30A/60A (Material (center body): ASTM B575, Tantalum, 316L SST)

#### Process connection: Top or bottom side

Unit: mm



# Model GTX30A/60A (Material (Meter body cover, Vent/Drain plugs: PVC))

## Process connection: Top or bottom side

Unit: mm



# **TERMINAL CONNECTION**

(Not applicable for Fieldbus. See SS2-GTX00Z-0100 for Fieldbus.)



Table 1: Terminal connection

Symbol	Details
S+	Power supply and output signal +
S-	Power supply and output signal –/Check meter –
CHK/AL	Check meter +
-	Ground

 Table 2: Terminal connection
 (option "Q7": Alarm output)

Symbol	Details
S+	Power supply and output signal +
S-	Power supply and output signal –
CHK/AL	Alarm +
<u> </u>	Ground/Alarm –

HART® is a registered trademark of the FieldComm Group. FOUNDATION™ is a trademark of the FieldComm Group.

Please read "Terms and Conditions" from the following URL before ordering and use. https://www.azbil.com/products/factory/order.html

Specifications are subject to change without notice.

# Azbil Corporation Advanced Automation Company

1-12-2 Kawana, Fujisawa Kanagawa 251-8522 Japan URL: https://www.azbil.com/

